## Data sheet 6ES7313-5BG04-0AB0



SIMATIC S7-300, CPU 313C, Compact CPU with MPI, 24 DI/16 DO, 4 AI, 2 AO, 1 Pt100, 3 high-speed counters (30 kHz), Integr. power supply 24 V DC, work memory 128 KB, Front connector (2x 40-pole) and Micro Memory Card required

General information	
HW functional status	01
Firmware version	V3.3
Engineering with	
Programming package	STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker, type C; min. 2 A; miniature circuit breaker type B, min. 4 A
Mains buffering	
<ul> <li>Mains/voltage failure stored energy time</li> </ul>	5 ms
Repeat rate, min.	1 s
Load voltage L+	
Digital inputs	
— Rated value (DC)	24 V
Reverse polarity protection	Yes
Digital outputs	
— Rated value (DC)	24 V
Reverse polarity protection	No
Input current	
Current consumption (rated value)	650 mA
Current consumption (in no-load operation), typ.	150 mA
Inrush current, typ.	5 A
l²t	0.7 A <sup>2</sup> ·s
Digital inputs	
from load voltage L+ (without load), max.	80 mA
Digital outputs	
from load voltage L+, max.	50 mA
Power loss	
Power loss, typ.	12 W
Memory	
Work memory	400.11
• integrated	128 kbyte
• expandable	No
Load memory	V
• Plug-in (MMC)	Yes
Plug-in (MMC), max.     Pata management on MMC (after last)	8 Mbyte
<ul> <li>Data management on MMC (after last</li> </ul>	10 a

programming), min.	
Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
<ul><li>without battery</li></ul>	Yes; Program and data
CPU processing times	
for bit operations, typ.	0.07 μs
for word operations, typ.	0.15 μs
for fixed point arithmetic, typ.	0.2 µs
for floating point arithmetic, typ.	0.72 μs
CPU-blocks	
Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks can
	be reduced by the MMC used.
DB	4.004.14.40000
• Number, max.	1 024; Number range: 1 to 16000
• Size, max.	64 kbyte
FB Number may	1 024: Number range: 0 to 7000
<ul><li>Number, max.</li><li>Size, max.</li></ul>	1 024; Number range: 0 to 7999
FC	64 kbyte
Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
OB	- · · · · · · · · · · · · · · · · · · ·
Number, max.	see instruction list
• Size, max.	64 kbyte
Number of free cycle OBs	1; OB 1
Number of time alarm OBs	1; OB 10
Number of delay alarm OBs	2; OB 20, 21
Number of cyclic interrupt OBs	4; OB 32, 33, 34, 35
Number of process alarm OBs	1; OB 40
Number of startup OBs	1; OB 100
Number of asynchronous error OBs	4; OB 80, 82, 85, 87
Number of synchronous error OBs	2; OB 121, 122
Nesting depth	
<ul> <li>per priority class</li> </ul>	16
<ul> <li>additional within an error OB</li> </ul>	4
Counters, timers and their retentivity	
S7 counter	
Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255
— preset	Z 0 to Z 7
Counting range	
— lower limit	0
— upper limit	999
IEC counter	
• present	Yes
• Type	SFB
• Number	Unlimited (limited only by RAM capacity)
S7 times	050
Number  Retentivity	256
Retentivity	Von
— adjustable — lower limit	Yes 0
	255
— upper limit	
— preset Time range	No retentivity
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
• present	Yes
• Type	SFB
764	

Number	Unlimited (limited only by RAM capacity)
Data areas and their retentivity	
Retentive data area (incl. timers, counters, flags), max.	64 kbyte
Flag	
• Size, max.	256 byte
Retentivity available	Yes; MB 0 to MB 255
<ul> <li>Retentivity preset</li> </ul>	MB 0 to MB 15
<ul> <li>Number of clock memories</li> </ul>	8; 1 memory byte
Data blocks	
<ul> <li>Retentivity adjustable</li> </ul>	Yes; via non-retain property on DB
Retentivity preset	Yes
Local data	
per priority class, max.	32 kbyte; Max. 2048 bytes per block
Address area	
I/O address area	
<ul><li>Inputs</li></ul>	1 024 byte
Outputs	1 024 byte
of which distributed	
— Inputs	none
— Outputs	none
Process image	1 024 buto
• Inputs	1 024 byte
Outputs     Inputs adjustable	1 024 byte
<ul><li>Inputs, adjustable</li><li>Outputs, adjustable</li></ul>	1 024 byte 1 024 byte
Inputs, default	128 byte
Outputs, default	128 byte
Default addresses of the integrated channels	,
— Digital inputs	124.0 to 126.7
— Digital outputs	124.0 to 125.7
— Analog inputs	752 to 761
— Analog outputs	752 to 755
Digital channels	
<ul><li>Inputs</li></ul>	1 016
<ul><li>of which central</li></ul>	1 016
<ul> <li>Outputs</li> </ul>	1 008
— of which central	1 008
Analog channels	
<ul><li>Inputs</li></ul>	253
— of which central	253
• Outputs	250
— of which central	250
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	none
• via CP	4
Number of operable FMs and CPs (recommended)	0
• FM	8
• CP, PtP	8
CP, LAN Rack	
• Racks, max.	4
Modules per rack, max.	8; In rack 3 max. 7
Time of day	o, don o max. i
Clock  Hardware clock (real time)	Voc
Hardware clock (real-time)     retentive and synchronizable	Yes Yes
<ul><li>retentive and synchronizable</li><li>Backup time</li></ul>	6 wk; At 40 °C ambient temperature
Deviation per day, max.	10 s; Typ.: 2 s
Behavior of the clock following POWER-ON	Clock continues running after POWER OFF
Behavior of the clock following expiry of backup	the clock continues at the time of day it had when power was switched
period	off

Operating hours counter	
Operating hours counter  • Number	1
	1
Number/Number range     Denga of values	
Range of values	0 to 2^31 hours (when using SFC 101)
Granularity	1 h
• retentive	Yes; Must be restarted at each restart
Clock synchronization	V
• supported	Yes
• to MPI, master	Yes
• to MPI, slave	Yes
• in AS, master	Yes
• in AS, slave	No
Digital inputs	
Number of digital inputs	24
<ul> <li>of which inputs usable for technological functions</li> </ul>	12
integrated channels (DI)	24
Input characteristic curve in accordance with IEC 61131,	Yes
type 1	
Number of simultaneously controllable inputs	
horizontal installation	
— up to 40 °C, max.	24
— up to 60 °C, max.	12
vertical installation	
— up to 40 °C, max.	12
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-3 to +5V
• for signal "1"	+15 to +30 V
Input current	
• for signal "1", typ.	8 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.1 / 0.3 / 3 / 15 ms (You can reconfigure the input delay of the standard inputs during program runtime. Please note that under certain circumstances your newly set filter time may not be effective until the next filter cycle.)
— Rated value	3 ms
for technological functions	
— at "0" to "1", max.	16 µs; Minimum pulse width/minimum pause between pulses at
	maximum counting frequency
Cable length	
• shielded, max.	1 000 m; 100 m for technological functions
• unshielded, max.	600 m; for technological functions: No
for technological functions	
— shielded, max.	100 m; at maximum count frequency
— unshielded, max.	not allowed
Digital outputs	
	16
Number of digital outputs	16
of which high-speed outputs     integrated sharmels (DQ)	4; Notice: You cannot connect the fast outputs of your CPU in parallel
integrated channels (DO)	16
Short-circuit protection	Yes; Clocked electronically
Response threshold, typ.	1 A
Limitation of inductive shutdown voltage to	L+ (-48 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
• on lamp load, max.	5 W
Load resistance range	
<ul><li>lower limit</li></ul>	48 Ω
upper limit	4 kΩ
Output voltage	
● for signal "1", min.	L+ (-0.8 V)
Output current	
<ul><li>● for signal "1" rated value</li></ul>	500 mA
<ul><li>for signal "1" rated value</li><li>for signal "1" permissible range, min.</li></ul>	500 mA 5 mA

<ul><li>for signal "1" permissible range, max.</li></ul>	0.6 A
<ul><li>for signal "1" minimum load current</li></ul>	5 mA
for signal "0" residual current, max.	0.5 mA
Parallel switching of two outputs	
• for uprating	No
for redundant control of a load	Yes
Switching frequency	
<ul> <li>with resistive load, max.</li> </ul>	100 Hz
with inductive load, max.	0.5 Hz
• on lamp load, max.	100 Hz
of the pulse outputs, with resistive load, max.	2.5 kHz
Total current of the outputs (per group)	
horizontal installation	
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	4.000
• shielded, max.	1 000 m
• unshielded, max.	600 m
Analog inputs	
Number of analog inputs	4
<ul> <li>For voltage/current measurement</li> </ul>	4
<ul> <li>For resistance/resistance thermometer</li> </ul>	1
measurement	
integrated channels (AI)	5; 4x current/voltage, 1x resistance
permissible input voltage for current input (destruction limit), max.	5 V; Permanent
· ·	20 V: Parmanant
permissible input voltage for voltage input (destruction limit), max.	30 V; Permanent
permissible input current for voltage input (destruction	0.5 mA; Permanent
limit), max. permissible input current for current input (destruction	50 mA; Permanent
limit), max.	
Electrical input frequency, max.	400 Hz
No-load voltage for resistance-type transmitter, typ.	3.3 V
Constant measurement current for resistance-type	1.25 mA
transmitter, typ.	.,
Technical unit for temperature measurement adjustable	Yes; Degrees Celsius / degrees Fahrenheit / Kelvin
Input ranges	V - 40 V 400 LO 0 V 40 V 400 LO
• Voltage	Yes; $\pm 10 \text{ V} / 100 \text{ k}\Omega$ ; 0 V to 10 V / 100 k $\Omega$
• Current	Yes; $\pm 20$ mA / $100$ $\Omega$ ; 0 mA to 20 mA / $100$ $\Omega$ ; 4 mA to 20 mA / $100$ $\Omega$
Resistance thermometer	Yes; Pt 100 / 10 MΩ
Resistance	Yes; 0 $\Omega$ to 600 $\Omega$ / 10 M $\Omega$
Input ranges (rated values), voltages	Voc
• 0 to +10 V	Yes
<ul><li>— Input resistance (0 to 10 V)</li></ul>	100 kΩ
Input ranges (rated values), currents	
Input ranges (rated values), currents  • 0 to 20 mA	Yes
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)	Yes 100 Ω
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA	Yes 100 Ω Yes
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)	Yes 100 $\Omega$ Yes 100 $\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA	Yes $100~\Omega$ Yes $100~\Omega$ Yes
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)	Yes 100 $\Omega$ Yes 100 $\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer	Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100	Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)	Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$ Yes $100 \ \Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $10~M\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms  — Input resistance (0 to 600 ohms)	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms  — Input resistance (0 to 600 ohms)  Thermocouple (TC)	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $10~M\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms  — Input resistance (0 to 600 ohms)  Thermocouple (TC)  Temperature compensation	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $10~M\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms  — Input resistance (0 to 600 ohms)  Thermocouple (TC)  Temperature compensation  — parameterizable	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $10~M\Omega$
Input ranges (rated values), currents  • 0 to 20 mA  — Input resistance (0 to 20 mA)  • -20 mA to +20 mA  — Input resistance (-20 mA to +20 mA)  • 4 mA to 20 mA  — Input resistance (4 mA to 20 mA)  Input ranges (rated values), resistance thermometer  • Pt 100  — Input resistance (Pt 100)  Input ranges (rated values), resistors  • 0 to 600 ohms  — Input resistance (0 to 600 ohms)  Thermocouple (TC)  Temperature compensation	Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $100~\Omega$ Yes $10~M\Omega$

— for resistance thermometer	Pt 100
Cable length	1,100
• shielded, max.	100 m
Analog outputs	
Number of analog outputs	2
integrated channels (AO)	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	55 mA
Current output, no-load voltage, max.	14 V
Output ranges, voltage	
• 0 to 10 V	Yes
• -10 V to +10 V	Yes
Output ranges, current	
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
for voltage output two-wire connection	Yes; Without compensation of the line resistances
for voltage output four-wire connection	No V
• for current output two-wire connection	Yes
Load impedance (in rated range of output)	410
with voltage outputs, min.	1 kΩ
with voltage outputs, capacitive load, max.	0.1 μF
with current outputs, max.      with current outputs, industrial lead may.	300 Ω
with current outputs, inductive load, max.  Postruction limits against externally copylind voltages and outputs.	0.1 mH
<ul> <li>Destruction limits against externally applied voltages and cur</li> <li>Voltages at the outputs towards MANA</li> </ul>	16 V; Permanent
Current, max.	50 mA; Permanent
Cable length	oo nia, i emanent
• shielded, max.	200 m
Analog value generation for the inputs	200 111
B. d. a. a	
Measurement principle	Actual value encryption (successive approximation)
Integration and conversion time/resolution per channel	
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.	12 bit
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable	12 bit Yes; 16.6 / 20 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.	12 bit
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference	12 bit Yes; 16.6 / 20 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  Fincoder  Connection of signal encoders  for voltage measurement	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for inductive load  Fincoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for inductive load  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for inductive load  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for inductive load  for inductive load  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for inductive load  for inductive load  Fincoder  Connection of signal encoders  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for inductive load  Fincoder  Connection of signal encoders  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire connection	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for inductive load  for inductive load  Fincoder  Connection of signal encoders  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for inductive load  for inductive load  Fincoder  Connection of signal encoders  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire connection  for resistance measurement with four-wire	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for ourrent measurement  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire connection  for resistance measurement with four-wire connection	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for repacitive load  for inductive load  for inductive load  Encoder  Connection of signal encoders  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire connection  for resistance measurement with four-wire connection  for resistance measurement with four-wire connection  Connectable encoders  2-wire sensor  — permissible quiescent current (2-wire sensor),	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No No
Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Time constant of the input filter  Basic execution time of the module (all channels released)  Analog value generation for the outputs  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Conversion time (per channel)  Settling time  for resistive load  for capacitive load  for inductive load  for inductive load  for outrent measurement  for current measurement as 2-wire transducer  for current measurement as 4-wire transducer  for resistance measurement with two-wire connection  for resistance measurement with three-wire connection  for resistance measurement with four-wire connection  for resistance measurement with four-wire connection  Connectable encoders  2-wire sensor	12 bit Yes; 16.6 / 20 ms 50 / 60 Hz  0.38 ms 1 ms  12 bit 1 ms  0.6 ms 1 ms 0.5 ms  Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No No No

Temperature error (relative to input range), (+/-)	0.006 %/K
Crosstalk between the inputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to input	0.06 %
range), (+/-)	
Output ripple (relative to output range, bandwidth 0 to 50	0.1 %
kHz), (+/-)	0.450/
Linearity error (relative to output range), (+/-)	0.15 %
Temperature error (relative to output range), (+/-)	0.01 %/K
Crosstalk between the outputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to	0.06 %
output range), (+/-)	
Operational error limit in overall temperature range	4.0/
Voltage, relative to input range, (+/-)	1 %
<ul> <li>Current, relative to input range, (+/-)</li> </ul>	1 %
<ul> <li>Resistance, relative to input range, (+/-)</li> </ul>	1 %
<ul> <li>Voltage, relative to output range, (+/-)</li> </ul>	1 %
Current, relative to output range, (+/-)	1 %
Basic error limit (operational limit at 25 °C)	
<ul> <li>Voltage, relative to input range, (+/-)</li> </ul>	0.8 %; Linearity error ±0.06 %
<ul> <li>Current, relative to input range, (+/-)</li> </ul>	0.8 %; Linearity error ±0.06 %
<ul> <li>Resistance, relative to input range, (+/-)</li> </ul>	0.8 %; Linearity error ±0.2 %
Resistance thermometer, relative to input range, (+/-	0.8 %
)	
<ul> <li>Voltage, relative to output range, (+/-)</li> </ul>	0.8 %
<ul> <li>Current, relative to output range, (+/-)</li> </ul>	0.8 %
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =	interference frequency
Series mode interference (peak value of	30 dB
interference < rated value of input range), min.	
<ul> <li>Common mode interference, min.</li> </ul>	40 dB
Interfaces	
Number of industrial Ethernet interfaces	0
Number of PROFINET interfaces	0
Number of RS 485 interfaces	1; MPI
Number of No 400 interfaces	I, IVII I
Number of BS 422 interfaces	
Number of RS 422 interfaces	o o
1. Interface	0
1. Interface Interface type	Integrated RS 485 interface
1. Interface Interface type Isolated	0
1. Interface Interface type Isolated Interface types	Integrated RS 485 interface No
1. Interface Interface type Isolated Interface types  • RS 485	Integrated RS 485 interface No Yes
1. Interface Interface type Isolated Interface types	Integrated RS 485 interface No
1. Interface Interface type Isolated Interface types  • RS 485	Integrated RS 485 interface No Yes
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.	Integrated RS 485 interface No Yes
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max. Protocols	Integrated RS 485 interface No  Yes 200 mA
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI	Integrated RS 485 interface No  Yes 200 mA
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master	Integrated RS 485 interface No  Yes 200 mA  Yes No
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master  • PROFIBUS DP slave	Integrated RS 485 interface No  Yes 200 mA  Yes No No
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master  • PROFIBUS DP slave  • Point-to-point connection	Integrated RS 485 interface No  Yes 200 mA  Yes No No
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master  • PROFIBUS DP slave  • Point-to-point connection  MPI	Integrated RS 485 interface No  Yes 200 mA  Yes No No No
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master  • PROFIBUS DP slave  • Point-to-point connection  MPI  • Transmission rate, max.	Integrated RS 485 interface No  Yes 200 mA  Yes No No No
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No No
1. Interface Interface type Isolated Interface types  • RS 485  • Output current of the interface, max.  Protocols  • MPI  • PROFIBUS DP master  • PROFIBUS DP slave  • Point-to-point connection  MPI  • Transmission rate, max.  Services  — PG/OP communication	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No Yes Yes
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services — PG/OP communication — Routing	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No No No No No No
Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services — PG/OP communication — Routing — Global data communication — S7 basic communication	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No No No Yes Yes Yes Yes No Yes No Yes No Yes
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No Ves Yes Yes Yes No Yes
Interface type Isolated Interface types  RS 485  Output current of the interface, max.  Protocols  MPI  PROFIBUS DP master  PROFIBUS DP slave  Point-to-point connection  MPI  Transmission rate, max.  Services  PG/OP communication  Routing  Global data communication  S7 basic communication  S7 communication  S7 communication  S7 communication, as client	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No Yes Yes Yes No Yes Yes No Yes Yes No Yes Yes No Yes Yes Yes Yes Yes Yes; Only server, configured on one side No; but via CP and loadable FB
Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services — PG/OP communication — Routing — Global data communication — S7 basic communication — S7 communication — S7 communication, as client — S7 communication, as server	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No Ves Yes Yes Yes No Yes
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No  187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server  Protocols  PROFIsafe	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No Yes Yes Yes No Yes Yes No Yes Yes No Yes Yes No Yes Yes Yes Yes Yes Yes; Only server, configured on one side No; but via CP and loadable FB
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No  187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI Transmission rate, max.  Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server  Protocols  PROFIsafe	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No  187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
1. Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI  Transmission rate, max.  Services — PG/OP communication — Routing — Global data communication — S7 basic communication — S7 communication — S7 communication — S7 communication, as client — S7 communication, as server  Protocols  PROFIsafe communication functions / header	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No 187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI  Transmission rate, max. Services — PG/OP communication — Routing — Global data communication — S7 basic communication — S7 communication — S7 communication, as client — S7 communication, as server  Protocols  PROFIsafe  communication functions / header PG/OP communication	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No 187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection  MPI  Transmission rate, max. Services — PG/OP communication — Routing — Global data communication — S7 basic communication — S7 communication — S7 communication — S7 communication, as client — S7 communication, as server  Protocols  PROFIsafe  communication functions / header  PG/OP communication Data record routing	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No 187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols  MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services  PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication S7 communication, as client S7 communication, as server  Protocols  PROFIsafe  communication functions / header  PG/OP communication Data record routing Global data communication	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No No  187.5 kbit/s  Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
Interface Interface type Isolated Interface types  RS 485 Output current of the interface, max.  Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 communication S7 communication S7 communication, as client S7 communication, as server  Protocols PROFIsafe communication functions / header PG/OP communication Data record routing Global data communication Supported	Integrated RS 485 interface No  Yes 200 mA  Yes No No No No 187.5 kbit/s  Yes Yes Yes Yes Yes Yes; Only server, configured on one side No; but via CP and loadable FB Yes No Yes No Yes No Yes

<ul> <li>Number of GD packets, transmitter, max.</li> </ul>	8
<ul> <li>Number of GD packets, receiver, max.</li> </ul>	8
<ul> <li>Size of GD packets, max.</li> </ul>	22 byte
<ul> <li>Size of GD packet (of which consistent), max.</li> </ul>	22 byte
S7 basic communication	
<ul><li>supported</li></ul>	Yes
<ul> <li>User data per job, max.</li> </ul>	76 byte
<ul> <li>User data per job (of which consistent), max.</li> </ul>	76 byte; 76 bytes (with X_SEND or X_RCV); 64 bytes (with X_PUT or
27	X_GET as server)
S7 communication	v
• supported	Yes
• as server	Yes
as client	Yes; Via CP and loadable FB
User data per job, max.	180 byte; With PUT/GET
User data per job (of which consistent), max.	240 byte; as server
S5 compatible communication	Vacuuis CD and leadable FC
• supported	Yes; via CP and loadable FC
Number of connections	0
overall     usable for PG communication	8 7
usable for PG communication  — reserved for PG communication	1
reserved for PG communication     adjustable for PG communication, min.	1
adjustable for PG communication, min.  - adjustable for PG communication, max.	7
usable for OP communication	7
reserved for OP communication	1
adjustable for OP communication, min.	1
adjustable for OP communication, max.	7
usable for S7 basic communication	4
reserved for S7 basic communication	0
adjustable for S7 basic communication, min.	0
adjustable for S7 basic communication, max.	4
S7 message functions	
Number of login stations for message functions, max.	8; Depending on the configured connections for PG/OP and S7 basic
Number of logit stations for message functions, max.	
	communication
Process diagnostic messages	communication Yes
Process diagnostic messages simultaneously active Alarm-S blocks, max.	
simultaneously active Alarm-S blocks, max.	Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions	Yes 300
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block	Yes 300  Yes; Up to 2 simultaneously
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step	Yes; Up to 2 simultaneously Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints	Yes 300  Yes; Up to 2 simultaneously
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints Status/control	Yes; Up to 2 simultaneously Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints	Yes 300  Yes; Up to 2 simultaneously Yes 4
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints Status/control  • Status/control variable	Yes; Up to 2 simultaneously Yes 4 Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints Status/control  • Status/control variable • Variables	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing • Forcing	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing • Forcing • Forcing, variables	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing  • Forcing • Forcing, variables • Number of variables, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing • Forcing • Forcing • Forcing, variables • Number of variables, max.  Diagnostic buffer	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing • Forcing • Forcing • Forcing, variables • Number of variables, max.  Diagnostic buffer • present	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing • Forcing • Forcing • Forcing, variables • Number of variables, max.  Diagnostic buffer • present • Number of entries, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes Figure 1  Yes Figure 2  Yes Figure 2  Yes Figure 3  Yes Figure 3  Yes Figure 3  Yes Figure 4  Yes F
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing  • Forcing  • Forcing  • Forcing, variables • Number of variables, max.  Diagnostic buffer  • present • Number of entries, max. — adjustable	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes Inputs, outputs 10
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.  Forcing  • Forcing • Forcing, variables • Number of variables, max.  Diagnostic buffer  • present • Number of entries, max. — adjustable — of which powerfail-proof	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes Inputs, outputs 10  Yes 500 No 100; Only the last 100 entries are retained
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  Status/control variable  Variables  Number of variables, max.  of which status variables, max.  of which control variables, max.  Forcing  Forcing  Forcing  Forcing, variables  Number of variables, max.  Diagnostic buffer  present  Number of entries, max.  adjustable  of which powerfail-proof  Number of entries readable in RUN, max.	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes 500 No 100; Only the last 100 entries are retained 499
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  Status/control variable  Variables  Number of variables, max.  of which status variables, max.  of which control variables, max.  Forcing  Forcing  Forcing  Forcing, variables  Number of variables, max.  Diagnostic buffer  present  Number of entries, max.  adjustable  of which powerfail-proof  Number of entries readable in RUN, max.  adjustable	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes Inputs, outputs 10  Yes From 10 to 499  Yes; From 10 to 499
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  Status/control  Status/control variable  Variables  Number of variables, max.  of which status variables, max.  of which control variables, max.  Forcing  Forcing  Forcing  Forcing, variables  Number of variables, max.  Diagnostic buffer  present  Number of entries, max.  adjustable  of which powerfail-proof  Number of entries readable in RUN, max.  adjustable  preset	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes Inputs, outputs 10  Yes From 10 to 499  Yes; From 10 to 499
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  Status/control  Status/control variable  Variables  Number of variables, max.  of which status variables, max.  of which control variables, max.  Forcing  Forcing  Forcing  Forcing, variables  Number of variables, max.  Diagnostic buffer  present  Number of entries, max.  adjustable  of which powerfail-proof  Number of entries readable in RUN, max.  adjustable  preset  Service data	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499 10
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  Status/control  Status/control variable  Variables  Number of variables, max.  of which status variables, max.  of which control variables, max.  Forcing  Forcing  Forcing, variables  Number of variables, max.  Diagnostic buffer  present  Number of entries, max.  adjustable  of which powerfail-proof  Number of entries readable in RUN, max.  adjustable  preset  Service data  can be read out	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499 10
simultaneously active Alarm-S blocks, max.  Test commissioning functions  Status block Single step Number of breakpoints  Status/control  • Status/control variable  • Variables  • Number of variables, max.  — of which status variables, max.  — of which control variables, max.  Forcing  • Forcing  • Forcing, variables  • Number of variables, max.  Diagnostic buffer  • present  • Number of entries, max.  — adjustable  — of which powerfail-proof  • Number of entries readable in RUN, max.  — adjustable  — preset  Service data  • can be read out  Interrupts/diagnostics/status information	Yes; Up to 2 simultaneously Yes 4  Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14  Yes Inputs, outputs 10  Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499 10

Integrated Functions	
Frequency measurement	Yes
Number of frequency meters	3; up to 30 kHz (see "Technological Functions" manual)
controlled positioning	No
integrated function blocks (closed-loop control)	Yes; PID controller (see "Technological Functions" manual)
PID controller	Yes
Number of pulse outputs	3; Pulse width modulation up to 2.5 kHz (see "Technological Functions"
realiser of palee earpare	Manual)
Limit frequency (pulse)	2.5 kHz
Potential separation	
Potential separation digital inputs	
Potential separation digital inputs	Yes
between the channels	No
between the channels and backplane bus	Yes
Potential separation digital outputs	1 65
Potential separation digital outputs     Potential separation digital outputs	Yes
between the channels	Yes
<ul> <li>between the channels, in groups of</li> </ul>	8
between the channels and backplane bus  Potential senaration analog inputs	Yes
Potential separation analog inputs	Vee: common for analog I/O
<ul> <li>Potential separation analog inputs</li> <li>between the channels</li> </ul>	Yes; common for analog I/O
	No You
between the channels and backplane bus  Petential consession analog systems.	Yes
Potential separation analog outputs	Veg common for analog I/O
Potential separation analog outputs	Yes; common for analog I/O
between the channels	No
between the channels and backplane bus	Yes
Isolation	
Isolation tested with	600 V DC
Ambient conditions	
Ambient temperature during operation	
● min.	0 °C
• max.	60 °C
configuration / header	
Configuration software	
STEP 7	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with
• OTEL 7	HSP 203
STEP 7 Lite	No
configuration / programming / header	
Command set	see instruction list
Nesting levels	8
System functions (SFC)	see instruction list
System function blocks (SFB)	see instruction list
Programming language	
— LAD	Yes
— FBD	Yes
— STL	Yes
— SCL	Yes
— CFC	Yes
— GRAPH	Yes
— HiGraph®	Yes
Know-how protection	
User program protection/password protection	Yes
Block encryption	Yes; With S7 block Privacy
Dimensions	
	120 mm
Width	120 mm
Height	125 mm
Depth	130 mm
Weights	
Weight, approx.	660 g
last modified:	8/24/2021 🗗